



418815

- 1 -

00936962

JC03 Rec'd PCT/TO

18 SEP 2001

## MULTI-CHIP-MODULE

The invention presented here relates to a multi-chip-module with a base carrier, on which at least in some areas signal conductor tracks and signal contact surfaces are arranged in a single layer, and with at least one semiconductor component operating  
5 in the signal range connected with signal conductor tracks and signal contact surfaces.

Multi-chip-modules (MCM) in prior art serve for the highly integrated arrangement of semiconductor components operated in the signal range (i.e., computer components, memory components, I-O components, etc.). MCMs of this type  
10 comprise very fine structures of conductor tracks and contact surfaces, wherein semiconductor components mostly present in the form of unhoused chips are in connection with the contact surfaces. Several of these semiconductor components are arranged on a common base carrier. Within the technology, a series of differing designs of such MCMs exist, mentioned as examples shall be solely the EP 0871222  
15 A2, WO 97/22138, WO 97/20273 and EP 0856888 A2. Multi-chip-modules of this type, e.g., are arranged on printed circuit boards and contacted through corresponding supply lines of the printed circuit board. Common to all known MCMs, however, is that they exclusively relate to the combination of digital and/or analogue semiconductor components, which are operated with electric powers in the  
20 signal range and which as a rule are utilised for the outputting of control signals. The conductor tracks and contact surfaces have a small cross section and can be arranged in a single layer or multilayered on a suitable carrier material, so that depending on the case in question a structure in the sense of an MCM-L, an MCM-C or an MCM-

0936962-18901

5

15

20

	1970	1971	1972	1973	1974	1975	1976	1977	1978	1979	1980	1981	1982	1983	1984	1985	1986	1987	1988	1989	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307	2308	2309	2310	2311	2312	2313	2314	2315	2316	2317	2318	2319	2320	2321	2322	2323	2324	2325	2326	2327	2328	2329	2330	2331	2332	2333	2334	2335	2336	2337	2338	2339	2340	2341	2342	2343	2344	2345	2346	2347	2348	2349	2350	2351	2352	2353	2354	2355	2356	2357	2358	2359	2360	2361	2362	2363	2364	2365	2366	2367	2368	2369	2370	2371	2372	2373	2374	2375	2376	2377	2378	2379	2380	2381	2382	2383	2384	2385	2386	2387	2388	2389	2390	2391	2392	2393	2394	2395	2396	2397	2398	2399	2400	2401	2402	2403	2404	2405	2406	2407	2408	2409	2410	2411	2412	2413	2414	2415	2416	2417	2418	2419	2420	2421	2422	2
--	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	---

[illegible]

This objective is achieved in the case of a multi-chip-module mentioned at the beginning by the fact, that in addition on the base carrier at least in some areas power conductor tracks and power contact surfaces arranged in a single-layer are provided, at least one power electronics component operating in the power range is provided, which is connected with the at least one power conductor track, at least one power contact surface and at least one signal conductor track, and that the power conductor tracks have a larger cross section than the signal conductor tracks at least on the basis of greater thickness dimensions. The comparison of cross sections preferably shall not be referred to the overall cross section of all conductor tracks, but shall be referred to the individual cross section of the respective conductor track.

While from the printed circuit board technology it is known how to equip a base carrier with a conductive layer and subsequently by means of photo-lithography to create a conductor track structure on this carrier, wherein conductors of differing cross sections can be produced by differing conductor track widths, this process, however, cannot be transferred to the production of very much smaller and for this reason very much more finely structured MCMs. Because of the excessive widening of conductor tracks for the purpose of obtaining a suitable cross section, the high integration on an MCM would not be implementable.

In contrast to this, in accordance with the invention it is proposed to arrange power electronics components, which in the meantime are also available in small format, which are operated with a much higher power than the signal semiconductor

Furthermore, there is the possibility, that the at least one signal conductor track leading to a power electronics component essentially seamlessly verges into a power conductor track and/or power contact surface. If the same materials are utilised for the power electronic conductor tracks and the signal conductor tracks, then on the basis of suitable manufacturing methods a tight bond of these conductor tracks is produced, which is superior to all other contacting methods. The control signal therefore can be transmitted to the power electronics components with the utmost precision and without any interference. Connecting elements susceptible to malfunction, such as solder points, are therefore superfluous.

5

10

15

20

distributed over the individual contact surfaces, then these can have a correspondingly smaller cross section.

In order for the MCM to be able to be electrically connected to the outside, in accordance with a further embodiment signal connection contact surfaces and power connection contact surfaces for a respective external connection are provided, wherein the signal connection contact surfaces and the power connection contact surfaces essentially have the same height. As a result of the same height of these contact surfaces, the layout of the MCM is facilitated, because the contact surfaces additionally can be utilised for the positioning. In the case of correspondingly high contact surfaces, the MCM can be installed head first, so that the components arranged on the base carrier are automatically protected.

Another procedure for the equalisation of the differing heights of signal conductor tracks and power conductor tracks consists in arranging the signal contact surfaces and the power contact surfaces on the side opposite the semiconductor components and power electronics components (reverse side) of the base carrier, wherein the connection contact surfaces are in electrical connection with the opposite side (front side) through the conductor track sections, which pass through the base carrier. On the reverse side of the base carrier, the contact surfaces then can have a relatively low height independent of the height of the conductor tracks arranged on the front side, wherein the power contact surfaces are designed correspondingly larger. This, however, because of the space conditions prevailing on the reverse side does not prove to be a disadvantage.

An adequate protection for the power electronics components as well as a relatively flat construction height can be achieved by the value, which results from the height

05936969 122701

of a power conductor track minus the height of a contact surface in electrical contact with this power conductor track, being the same or greater than the height of the power electronics component contacting this power contact surface. This signifies, that the power conductor tracks protectively surround the electronic components and, because they are higher than them, provide a protection against shocks.

A further important aspect, which is important in the case of an integration of signal circuits and power circuits on an MCM, consists in the adequate heat dissipation. For this purpose it is possible to assure, that at least one heat conducting element is provided on the base carrier, which is in a thermally conductive connection with a power electronics component. This heat conducting element then conducts the superfluous heat away from the power electronics component, which thereupon can be dissipated through it in any suitable form.

For this purpose, provisions additionally can favourably be made, that at least one heat conducting element is connected with a heat exchanger device. The heat exchanger device then takes care of the corresponding dissipation of the heat in function of the power of the electronics component. Possible as heat exchanger devices are all means in miniature form suitable for this purpose, independent of whether a forced cooling or anything similar is provided. In order to also not excessively burden the front side of the MCM with the heat exchanger equipment, so that a high degree of integration is not impaired by this, it may also be arranged on the reverse side of the base carrier, wherein the heat conducting element passes through the base carrier. The heat conducting element therefore conducts the heat through the base carrier to the heat exchanger device arranged on the reverse side. This has advantages in particular in the case of MCMs installed head first, because the possibly tight installation conditions do not lead to a build-up of heat, because the heat is conducted into regions, where an adequate heat exchange can be provided for.

09036962 122701

In the case of a variant of the heat exchanger it is foreseen, that it comprises fine cooling ribs with a ratio of height to width of 0.1 to 10, in preference 1 to 4. Cooling ribs of this type are capable of being manufactured in a similar manner as the conductor tracks and therefore they have a relatively large ratio of height to width.

- 5 This with relatively small structures makes it possible to provide very high heat exchange rates.

- A further variant consists in the fact, that a heat exchanger device is connected with a power electronics component in an immediately thermally conductive manner. A cooling structure of this kind can be directly mounted on the power electronics components by means of correspondingly suitable means of connection, e.g., a thermally conductive adhesive.
- 10

- In order to be in a position to assure a standardisation, in accordance with an embodiment provisions are made, that the signal contact surfaces and the power contact surfaces are arranged grouped on the base carrier in such a manner, that the module can be inserted into a standardised base. Here there is also the possibility of grouping the contact surfaces in such a way, that bases, which are already present, can be utilised. These then solely have to have suitable contacts at the corresponding points for the connection of the power circuits.
- 15

- The invention furthermore is related to a method for the manufacture of a multi-chip-module. The method comprises the following steps:
- 20

Preparation of a base carrier with signal conductor tracks and signal contact surfaces, deposition of a structured layer, by which at least the signal conductor tracks and



signal contact surfaces are essentially covered except for connection points and which comprises a negative structure of the power conductor tracks and/or power contact surfaces.

- 5 Filling in the negative structures by means of a metallisation process for the creation of the power conductor tracks and/or contact power surfaces, wherein at the connection points a contacting of the signal conductor tracks and/or of the signal contact surfaces and of the power conductor tracks and/or power contact surfaces takes place.

- 10 As a result of the separate manufacturing of signal conductor tracks and power conductor tracks, structures with differing heights can be created with relatively simple process steps. The already present signal conductor tracks are covered and except for suitable contact points sealed off for the protection from the process steps to follow. The base material used by means of the most differing processes can be equipped with a negative structure, which predetermines the course of the power
- 15 conductor tracks. In preference, this structure goes right through to the base carrier, so that thereupon a coating of the base carrier in the zone of the negative structure can take place. For the metallisation taking place, also differing processes can be utilised. The structured layer defines the form of the power conductor tracks and corresponding contact surfaces, which are creatable by the metallisation. Thereafter
- 20 the structured layer protects the corresponding track - and contract structures during the manufacturing process.

- In preference, on the base carrier in the zone of the negative structure a conductive adhesive layer can be deposited, which serves as the base for the metallisation process. It is important, that an adequate connection between the base carrier and the
- 25 conductor track structures is produced. This preferably can be implemented by a more expensive adhesive layer, which effects the anchoring in a better manner. The

further adhesion is thereupon achievable by means of simple metallisation processes, because the adhesive layer possesses a corresponding conductivity.

- Favourably the structured layer can be deposited by means of a photo-lithographic process. Very fine structures with very advantageous ratios of height to width can be manufactured by means of such a process. The designing of conductor tracks and contact surfaces in a shape required is achieved in this manner.

In accordance with a variant of the method, the metallisation process can take place by galvanic deposition of metal. In particular in connection with a conductive adhesive layer, on this layer thereupon the desired structure can be created.

- 10 In the case of most applications it will be desirable, that in accordance with a variant, following the metallisation process the structured layer is removed.

In the following, examples of embodiments of the invention presented here are explained in more detail on the basis of drawings. These illustrate:

Fig. 1 A first embodiment of an MCM in a perspective view,

- 15 Fig. 2 a second embodiment of an MCM in a side view,

Fig. 3 a third embodiment of an MCM in a perspective view and

0936962-122701

Fig. 4 a fourth embodiment of an MCM in a perspective view.

The embodiment of an MCM illustrated in Fig. 1 in essence comprises a continuous, plate-shaped base carrier 1, on which very finely structured electrically conductive signal conductor tracks 2 as well as power conductor tracks 5 with a larger cross section are arranged. The signal conductor tracks 2 respectively lead to a signal contact surface 3, which is arranged at the edge of the base carrier 1, with which the signal zone of the MCM makes contact with the outside. Starting out from the signal connection contact surfaces 3, the signal conductor tracks 2 lead to signal contact surfaces 4, which serve for contacting signal semiconductor components 11. These signal semiconductor components 11 can be housed or unhoused chips. In Fig. 1, solely a single signal semiconductor component 11 is depicted. It goes without saying, that the signal zone can be as complicated as required and can be provided with the number of conductor tracks 2 and signal semiconductor components respectively required for the application purposes. The contacting of the signal semiconductor components 11 and the deposition of the signal conductor tracks 2 and of the contact surfaces 3 and 4 is well known. From the signal semiconductor component 11, additional signal conductor tracks or control lines 8 lead to the power zone of the MCM. These control lines 8 are in immediate contact with corresponding power contact surfaces 7. These power contact surfaces 7 are electrically isolated from power contact surfaces 7a, which are connected with the power conductor tracks 5. The power conductor tracks 5 on the edge of the base carrier 1 lead to power connection contact surfaces 6.

The material of the base carrier 1 depending on the application case can consist of fibre-glass reinforced plastic material (construction in the sense of an MCM-D) or of another suitable material (e.g., an electrically insulated metal). In the embodiment

illustrated, the conductor tracks 2, 8 and 5 are respectively arranged in a single layer. A multi-layered arrangement can be provided.

The connection contact surfaces 3 and 6 serve for the electrical connection of the complete MCM with the environment (e.g., motors to be driven, superordinate  
5 computers, sensors .....,etc.).

In the illustrated exemplary embodiment, the signal conductor tracks 2 are approx. 5 to 10 micrometers thick and the power conductor tracks approx. 0.6 to 0.7 mm thick. The width of the power conductor tracks is also a multiple of the width of the signal conductor tracks 2. In the depicted exemplary embodiment, the contact surfaces 7, 7a  
10 and 6 have the same height as the power conductor tracks 5. Mounted onto the contact surfaces is a power electronics component 12.

Because a large number of signal semiconductor components 11 and/or only individual power electronics components 12 generate relatively high temperatures, great significance has to be attached to a good heat dissipation. For this purpose, in  
15 the zones free of conductor tracks 2, 5 and contact surfaces 3, 4, 6, 7, 7a, at least, however, in the power zone, heat conducting elements 9 can be provided. The heat conducting element 9 illustrated in Fig. 1 is arranged between the power contact surfaces 7, 7a and is in a heat conducting contact with the bottom side of the power electronics component 12. For this purpose, the base carrier 1 is breached in such a  
20 manner, that the heat conducting element 9 passes through the base carrier 1 and thus makes a good heat dissipation to the reverse side of the base carrier 1 possible. The eduction of the heat then can take place in the most diverse and varied manner.

The control lines 8 in preference consist of the same material as the power contact surfaces 7, so that a tight connection without any interfering interfaces or connections is created. The high density of integration, which is achievable through the arrangement on the base carrier 1, permits previously inconceivable possibilities  
5 of the MCM technology.

In preference, the manufacture of these structures is effected in several steps through photo-lithographic processes in combination with galvanic deposition, so that independently of one another the signal zone and the power zone are produced. The free of any interference transition, however, then takes place at the interfaces.

- 10 In the following, on the basis of the Fig. 2 a second embodiment of an MCM is explained in more detail. Hereinafter, only the essential differences to the preceding exemplary embodiment are dealt with. For this reason, the same reference numbers designate the same or equivalent components. A corresponding description is transferable.
- 15 The second embodiment in accordance with Fig. 2 essentially comprises two great differences. The contact surfaces 3 and 6 are in connection with the reverse side of the base carrier 1, in which conductor track sections not depicted in more detail pass through the base carrier 1 at this point. Through this, on the reverse side contact elevations are produced, which correspondingly take over the task of the connection
- 20 contact surfaces 3 and 6. By means of the arrangement of the contact elevation 10 on the reverse side of the base carrier 1, these can be designed with the same height, however, with a differing surface area, as a result of which the contacting of the MCM is very much simplified. The contact elevations 10, e.g., can be provided with so-called solder bumps (i.e., with elevations of soldering tin with the shape of

segments of a sphere). In this manner it is assured, that the complete MCM in a single manufacturing step is simultaneously fixed onto a corresponding substrate and is capable of being electrically contacted by it.

5 The second difference consists of the fact, that on the electronics component 12 a heat sink 13 is positioned, which takes care of a corresponding heat dissipation. In order that this heat sink 13 does not increase the volume of the complete superstructure to too great an extent, it preferably is a body, the cooling structures of which consist of geometrical shapes (walls, columns, pyramids, etc.) with a high aspect ratio, i.e., with a great ratio of structural height to structural width. In this  
10 manner it is ensured, that the heat sink 13 in case of a very small overall height (e.g., 0.5 mm) provides a very large cooling surface area (e.g., in the case of a design of the cooling structures as columns 0.4 mm high a cooling surface area of 25 cm<sup>3</sup> per 1 cm<sup>2</sup> of base surface area).

15 In the case of superstructures of MCMs of this kind, over and above this there is the possibility of protecting the signal semiconductor components 11 and in particular the power electronics components 12 from mechanical effects from the outside, e.g., in that housings are provided or an encapsulation of the elements is implemented.

Also in the case of the exemplary embodiment explained in the following in accordance with Fig. 3, only the essential differences are dealt with, for which reason  
20 the preceding description is made reference to in complement.

Here the power connection contact surfaces 6 have the same height as the signal connection contact surfaces 3. For this purpose, the signal connection contact

surfaces 3 are designed as columns. These too, can be provided with contact elevations 10, so that a uniform height results. The power conductor tracks 5 in this almost have the same height as the power connection contact surfaces 6, while in contrast the power contact surfaces 7 and 7a are less thick. In doing so, however, it is assured, that the overall cross section of the power contact surfaces 7a is adequate for the power transmission. Also the heat conducting element 9 is correspondingly adapted according to the height of the power contact surfaces 7, 7a. The difference in height of the power contact surfaces 7, 7a and of the power conductor tracks 5 is calculated in such a manner, that a countersunk installation of the power electronic components 12 can be implemented. The whole superstructure of the MCM apart from the countersunk installation of the power electronics components also provides the possibility, that it can be installed with its top side facing downwards. In doing so, once again the installation of the connection contact surfaces 3, 6 with the same height alleviates the contacting. By means of this kind of assembly of the complete MCM, a complete protection of the semiconductor components 11, 12 against mechanical damage results, so that these - if at all - only have to be protected against humidity and harmful chemicals with a thin passivation layer.

The heat conducting elements 9 once again pass through the base carrier 1 and are in connection with a heat sink 13, which is located on the reverse side of the base carrier 1. The heat sink 13 in preference once again comprises cooling structures made of geometrical shapes (walls, columns, pyramids, etc.) with a high aspect ratio. Because this type of heat sink 13 makes available an extremely large cooling surface area, the installation with the top side facing downwards does not present the danger of overheating, even if these components are thereupon integrated in closed-off units, because the heat is adequately dissipated to the outside.

Also in the case of the exemplary embodiment in accordance with Fig. 4, only the most significant differences to the preceding exemplary embodiments are dealt with, for which reason here too, reference is made to the description above with respect to structurally identical elements. In the case of this exemplary embodiment, all signal  
5 connection contact surfaces 3 and power connection contact surfaces 6 are designed as column contacts at the edge of the base carrier 1. This arrangement corresponds to a standardisation, so that the MCM as an „intelligent power module“ can be plugged into bases available on the market as standard components.

In Fig. 4 it is also very clearly evident, that the routing of the power conductor tracks  
10 5 can be designed in any way required, so that the predefined positions of the connection contact surfaces 6 can be reached. The base carrier 1 and the outside connection contact surfaces 3 necessary for the contacting of the whole MCM can be constructed and shaped in such a manner, that the desired standard geometry is provided. The embodiment according to Fig. 4, for example, corresponds to a so-  
15 called „chip-carrier“ module (PLCC module) with 15 contact points on its edge. In a similar fashion, without any problem PLCCs with 20, 28, ... 84 poles or PGA-compatible superstructures or any other standard superstructures can be made available. In such cases, where the cross sections of the individual standard contacts is not sufficient to conduct the necessary power to the power electronics components  
20 12, several power conductor tracks for one and the same power contact surfaces 7a can be split-up over several power connection contact surfaces 6 designed as standard contacts, so that overall a sufficiently great conductor cross section is obtained.

0936559 123701